



## PUSH PLATE SWITCHES - WIRELESS AND HARDWIRED

**For Handicap Access, Automatic Door Activation & Request-to-Exit Applications**

- **Door Opener Activation**
- **Access Control Request-to-Exit (RTE)**
- **Wireless Versatility**
- **Automatic Door Sequencer Activation**



### Features



- Mounting Plate:** Heavy Duty 1/8" (3.2mm) mounting plate
- Faceplate:** Heavy 18 Gauge (1.02mm), 630/US32D Satin Stainless Steel Standard
- Legends:** Bold debossing or engraving with black or blue infill
- Contacts:** SPDT or DPDT, 15 Amps @ 125/250VAC; UL 1054, CSA Listed
- Depth:** [Narrow & (1) Gang] SPDT-7/8" deep, DPDT-1-3/8" deep, [4 1/2", & 6" square/ round] SPDT-3/4" deep, DPDT-1-5/32" deep



### 1-11/16" Narrow Mullion Push Plate Switch – Recessed, Surface Box or Bollard Mount

- Designed to flush-mount directly into narrow jamb
- Requires narrow mullion prep

#### Models

- 482O1U** Push to Open, black infill, **SPDT**
- 482A1U**  Push to Open, blue infill, **SPDT**
- 484O1U** Push to Open, black infill, **DPDT**
- 484A1U**  Push to Open, blue infill, **DPDT**

#### Accessories



- 400-1B** Narrow Mullion Surface Box, 1-3/4" x 4-9/16" x 1-3/4" O.D.



### 2 3/4" x 4 1/2" Single (1) Gang Push Plate Switch


- Pressing any part of the push plate (2 3/4" x 4 1/2") causes switch actuation
- Surface Box or Bollard Mount
- Depth: SPDT - 3/4" deep; DPDT - 1 1/2" deep

#### Models

- 482O2U** Push to Open, black infill, **SPDT**
- 482A2U**  Push to Open, blue infill, **SPDT**
- 484O2U** Push to Open, black infill, **DPDT**
- 484A2U**  Push to Open, blue infill, **DPDT**

#### Accessories

- 480-2SB** Surface mount box 2 3/4" x 4 1/2" x 1 5/8" O.D.





 = can be used with wireless transmitter and receiver



## 4 1/2" x 4 1/2" Square Push Plate Switches

- Pressing any part of the push plates 4 1/2" x 4 1/2" active area causes switch actuation
- 1 Gang or 2 gang recessed or Surface Box Mount • Depth: SPDT 5/8" deep; DPDT 1 1/2" deep

### Models

<b>482O4U</b>	Push to Open, black infill, <b>SPDT</b>
<b>482A4U</b>	 Push to Open, blue infill, <b>SPDT</b>
<b>484O4U</b>	Push to Open, black infill, <b>DPDT</b>
<b>484A4U</b>	 Push to Open, blue infill, <b>DPDT</b>

### Accessories



<b>480-4FB</b>	Square Flush Recessed box, 1-gang, 6 3/4" x 6 3/4" x 1 7/8" O.D.
<b>480-4SBB</b>	Surface mount box, 4-1/2" x 4-1/2" x 1 3/4" O.D. with Battery compartment for wireless
<b>480-4SB</b>	Surface mount box, 4-1/2" x 4-1/2" x 1 7/8" O.D.
<b>480-4SE</b>	3-sided stainless shroud for exterior applications, 4-11/16" x 4-7/8" x 1/2"



## 6" x 6" Square Push Plate Switch

- Pressing any part of the push plates 6" x 6" active area causes switch actuation
- 1 Gang or 2 gang recessed or Surface Box Mount • Depth: SPDT 5/8" deep; DPDT 1 1/2" deep

### Models

<b>482O6U</b>	Push to Open, black infill, <b>SPDT</b>
<b>482A6U</b>	 Push to Open, blue infill, <b>SPDT</b>
<b>484O6U</b>	Push to Open, black infill, <b>DPDT</b>
<b>484A6U</b>	 Push to Open, blue infill, <b>DPDT</b>

### Accessories



<b>480-6SBB</b>	Surface mount box, 2-gang Battery Compartment, 4 1/2" x 4 1/2" x 1 3/4" O.D.
-----------------	--



## 4 1/2" Round Push Plate Switch

- Pressing any part of the push plates 4 1/2" active area causes switch actuation
- 1 Gang or 2 gang recessed or Surface Box Mount • Depth: SPDT 5/8" deep; DPDT 1 1/2" deep

### Models

<b>482O4RU</b>	Push to Open, black infill, <b>SPDT</b>
<b>482A4RU</b>	 Push to Open, blue infill, <b>SPDT</b>
<b>484O4RU</b>	Push to Open, black infill, <b>DPDT</b>
<b>484A4RU</b>	 Push to Open, blue infill, <b>DPDT</b>

### Accessories



<b>480-4RSB</b>	Surface box, 5" Dia., 2 1/8" O.D.
<b>480-4RG</b>	4" round gasket
<b>480-4RFB</b>	Recessed Mount Box, 5 7/8" overall diameter with trim ring
<b>480-4RRB</b>	Surface Escutcheon, 7 7/8" Dia., 1 9/16" overall height



## 6" Round Push Plate Switch

- Pressing any part of the push plates 6" active area causes switch actuation
- 1 Gang or 2 gang recessed or Surface Box Mount • Depth: SPDT 5/8" deep; DPDT 1 1/2" deep

### Models

<b>482O6RU</b>	Push to Open, black infill, <b>SPDT</b>
<b>482A6RU</b>	 Push to Open, blue infill, <b>SPDT</b>
<b>484O6RU</b>	Push to Open, black infill, <b>DPDT</b>
<b>484A6RU</b>	 Push to Open, blue infill, <b>DPDT</b>

### Accessories

<b>480-6RSB</b>	Surface box Round, 6 7/16" Dia., 2 1/8" O.D.
<b>480-6RG</b>	6" round gasket
<b>480-6RFB</b>	Recessed Flush Escutcheon, 7 3/4" overall diameter with trim ring





## INGRESS-R.E.X TOUCH PANEL COLUMN



**9" x 6" Ingress-R.E.X Touch Panel Column**  
**Fully Active 22-1/2 Sq. Inch Actuation Area**  
Recommended Centerline mounting height 34" to 48"

**Material:** Sturdy 1/8" extrusion with architectural finish  
**Overall Size:** 9" h x 6" w x 1-1/2" d (229 x 152 x 38mm)  
**Active Area:** 9" h x 2-1/2" w (229 x 63.5mm)

### Models

- 482AA9 Push to Open, black infill, **SPDT**
- 484AA9 Push to Open, black infill, **DPDT**

### Finish

- V 628 Aluminum (*standard*), blue infill
- X 710 Dark Anodized Aluminum, white infill



**36" x 6" Ingress-R.E.X Touch Panel Column Fully Active 90 Sq. Inch Actuation Area**  
Recommended mounting height is 3" from floor

**Material:** Sturdy 1/8" extrusion with architectural finish  
**Overall Size:** 36" h x 6" w x 1-1/2" d (914 x 152 x 38mm)  
**Active Area:** 36" h x 2-1/2" w (914 x 63.5mm)

### Models

- 482AA36 Push to Open, black infill, **SPDT**
- 484AA36 Push to Open, black infill, **DPDT**

### Finish

- V 628 Aluminum (*standard*), blue infill
- X 710 Dark Anodized Aluminum, white infill



= can be used with wireless transmitter and receiver

## WIRELESS TRANSMITTER & RECEIVER

For Remote Control Versatility for Touch Panel Column and Push Plate Switches.  
75 foot wireless range. less barriers.

### 433MHz Micro Transmitter

- Requires a non-metallic surface box or standard bollard cap (non-metallic)
- Pre-Wired for quick installation
- Antenna magnifies signal
- **Voltage Input:** 9V Battery (included)
- **Trigger Input:** Momentary, N.O.Dry Contact
- **Temperature:** -20F — 100F
- **Dimensions:** 1-9/64" x 15/16" x 7/32" (29 x 49 x 6mm)
- Works with 400RC433

### Models

400W1-433 433MHz Micro Transmitter

### 433MHz 1 Channel Nano Receiver

Designed to control automatic door or electrified locking hardware with code-hopping technology for increased security.

- **Carrier Frequency:** 433.92 MHz
- **Relay Numbers:** 1
- **Temperature:** -4F — 158F
- Works with 400W1-433
- **Power Supply:** 12/24 VAC/DC
- **Contacts:** C-NO
- **Dimensions:** 1-1/4" x 2" x 3/4" Deep (32 x 51 x 19mm)

### Models

400RC433 433MHz 1 Channel Receiver





S and D prep



P prep

## **BOLLARD POST WITH PUSH PLATE OR TOUCH PANEL**

- **For Use With Push Plates, Touch Panel Columns & Exit Switches**
- **6" square with 1/8" walls**
- **42" surface mount or 54" in-ground**

### **Application**

Alternative to wall mounted access control or switches for entry doors. Bollard post provide visibility and meet accessibility guidelines. Practical solution for surface mount or in-ground installation.

### **Features**

- For use with Push Plates, Touch Panel Columns & Exit Switches
- 6" square with 1/8" walls
- Black HDPE mortised removable cap with secure transmitter mount
- Standard single gang prep located at 36" from finished floor
- Surface mount (42") or In-Ground mount (54")

### **Models**

**BPS6** 42" surface mount, 6" square post  
**BPG6** 54" in-ground, 6" square post

### **Prep**

**S** 1-gang prep  
**D** 2-gang prep  
**P** Touch Panel prep  
**A** Narrow Mullion Prep

### **Finish**

**V** 628 Aluminum (*standard*)  
**X** 710 Dark Anodized Aluminum