

# 6160RF

## DELUXE CUSTOM ALPHA INTEGRATED KEYPAD/RECEIVER



WITH DOOR ATTACHED

The 6160RF's integrated keypad and receiver design helps reduce installation, material and inventory costs while increasing valuable add-on opportunities. It adds full wireless capability to any VISTA control without additional wiring or sacrificing zones and can help close sales by easily adding 5804, 5804BDV or 5878 wireless interfaces for end-user remote convenience.

Dealers can add the 5828 and 5828V wireless keypads to VISTA for the first time, presenting a tremendous upsell opportunity by letting them offer their customers secondary wireless keypads on every installation with virtually no install time.

## FEATURES

- 6160 Custom Alpha Keypad
- Built in 5881ENH unlimited zone wireless receiver
- Compatible with 5828/5828V wireless keypads on VISTA systems\*
- Single four-wire run is all that's required
- It is the ideal choice where wireless keys are to be used:
  - Keys can be programmed at the panel, just as they would with the 5881ENH
- Fully compatible with all 5800 wireless devices including bidirectional devices\*

- The 5800TM Module needed to support the 5804BD and 5804BDV is already built-in
- Supports encrypted operation of the 5804E and 5804BDV four-button keys

### Easy to Operate

- The custom alpha display is easy to read, with large characters and simplified descriptions
- The sounder beeps to help identify security system status

- Comfortable soft-touch keys labeled with simple commands are illuminated for nighttime visibility
- Four larger function keys can be programmed for one touch operation and are accessible even when the door is closed

### Stylishly Designed

- Sleek, white design blends with any décor
- Contoured, removable door lets customers customize the keypad for the look they want
- With the door closed the keypad has a smooth, unobtrusive appearance

\*Not compatible with 5839

## SPECIFICATIONS

### Dimensions

- 5 5/16" H x 7 3/8" W x 1 3/16" D (135mm x 190mm x 30mm)

### Sounder

- Piezoelectric

### Wiring

- - (Black): Ground
- + (Red): +12 VDC (Aux. Power)
- D1 (Green): "Data In" to control panel
- D0 (Yellow): "Data out" from control panel

### Current

- Standby: 50ma
- Activated: 150ma

### Compatibility

- Fully compatible with all VISTA controls

## ORDERING:

<b>6160RF</b>	Keypad/Receiver
<b>5828</b>	Wireless Fixed English Keypad
<b>5828V</b>	Wireless Talking Fixed English Keypad

## Honeywell Security & Custom Electronics

Honeywell  
2 Corporate Center Drive Suite 100  
P.O. Box 9040  
Melville, NY 11747  
www.honeywell.com

L/6160RF/D  
September 2007  
© 2007 Honeywell International Inc.

# Honeywell