

ARD-R10 - iCLASS/MIFARE Reader



- Compact reader with beeper and multicolored LED column display
- ► Plastic-coated for indoor and outdoor mounting
- Currency consumption 65 mA/medium, 225 mA peak at 12 V
- ▶ 50 cm connection cable

Non-contact access control readers in 13.56 MHz technology for connecting to an access controller with Wiegand interfaces.


This reader is suitable for mullion installation and for indoor and outdoor use.

As well as reading iCLASS proximity cards that work with diversified keys of 64-bit length for two-way authentication, the reader makes it possible to read serial numbers in 32-bit format in line with ISO standard 14443A.

Encrypted data is transmitted between the reader and card.

Installation/Configuration Notes

Installation



- Four Wiegand interfaces for connecting readers.
- Up to four readers can be installed per entrance.

Please follow the general mounting instructions for the proximity reader regarding the distance between readers and metallic surfaces.

Parts Included

Quantity Component

1 Reader body with board Mounting material 1 1 Installation guide

Technical Specifications

Housing

External dimensions (W x H x D) 102.6 x 48.3 x 20.3 mm Material Polycarbonate (UL 94)

Color Black Weight $90.7\,\mathrm{g}$

Connections

Display Multicolored LED

Interfaces Wiegand

Environmental conditions

Operating temperature -35° to 65°C

Humidity 5 to 95% no condensation water

Environment class IP 55

Electrical parameters

Power supply 10 to 16 VDC Reading process IClass, MIFARE CSN

13.56 MHz Operating/modulation frequency

Reading distance 5 cm to 7.6 cm with iCLASS card

2.5 cm with iCLASS TAG or key fob

Ordering Information

ARD-R10 - iCLASS/MIFARE Reader ARD-R10EMEA-000

Non-contact compact reader with beeper and multicolored LED display for Wiegand interfa-

ces.

Accessories

ARD-R10-AP-G Surface-Mount Panel

F01U508789

Surface-mount panel for ARD-R10 reader. 10 items/packaging unit.

Americas:
Bosch Security Systems, Inc.
130 Perinton Parkway
Fairport, New York, 14450, USA
Phone: +1 800 289 0096
Fax: +1 585 223 9180 security.sales@us.bosch.com www.boschsecurity.us

Europe, Middle East, Africa:

Bosch Security Systems B.V. P.O. Box 80002 F.O. Box 60002 5600 JB Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

Asia-Pacific: Rep Robert Bosch (SEA) Pte Ltd, Security Systems Represented by 11 Bishan Street 21 Singapore 573943 Phone: +65 6258 5511 Fax: +65 6571 2698 apr.securitysystems@bosch.com www.boschsecurity.com