

# DS1109i Glassbreak Detector

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Microprocessor-based SAT
- ▶ Automatic environmental test circuitry
- ▶ Built-in door or window contact

The DS1109i Detector uses microprocessor-based sound analysis technology (SAT) to listen for the specific frequencies associated with breaking glass. It can be used to detect breakage of plate, tempered, laminated and wired glass types. A built-in environmental test feature alerts the installer of false alarm hazards in harsh environments. It is specially designed to mount on door or window frames. A built-in magnetic contact allows monitoring of a door or window opening.

## Functions

### Signal Processing

Audio signals are analyzed using microprocessor-based SAT and must produce specific frequency, signature, and timing relationships to cause an alarm. The sophistication of this processing technique insures proper catch performance while eliminating false alarms.

### Test Features

The push button operated test mode provides a location verification and operational test when using the optional DS1110i glassbreak tester. Test mode also includes an environmental test that alerts the installer to possible false alarm sources caused by ambient noise. Automatic sound check feature allows the end user to verify that the detector is powered and

functioning by clapping his hands. Externally visible alarm LED indicates an alarm or test condition and can be programmed to latch if desired.

## Certifications and approvals

Region	Certification
Europe	CE 2004/108/EC EMC Directive (EMC); 2006/95/EC Low-Voltage Directive (LVD); 2011/65/EU Restriction of the use of certain hazardous substances in electrical and electronic equipment (RoHS)

## Installation/configuration notes



### Notice

Glassbreak detectors are intended only as a component of a perimeter protection system. They should always be used in conjunction with motion sensors.

### Mounting

Mount the DS1109i on the ceiling, or on the wall opposite or, adjacent to the window. Coverage depends on room acoustics and window size.

**Standard Coverage**

3 m (10 ft) for glass sizes over 30.5 cm x 30.5 cm (12 in. x 12 in.).

**Technical specifications****Electrical**

Current:	21 mA nominal at 12 VDC
Voltage:	9 VDC to 15 VDC

**Mechanical**

Dimensions:	3.2 cm x 9.5 cm x 2.3 cm (1.25 in. x 3.75 in. x 0.88 in.)
Material:	High impact ABS plastic enclosure
Alarm Output:	Normally-closed reed relay rated at 3.5 W, 125 mA at 28 VDC for resistive loads.
Tamper Output:	Normally-closed cover activated tamper switch with separate terminals. Contacts rated at 28 VDC, 125 mA maximum

**Environmental**

Operating Temperature:	-29°C to +49°C (-20°F to +120°F)
Radio Frequency Interference (RFI) Immunity:	No alarm or setup on critical frequencies in the range from 26 MHz to 950 MHz at 50 V/m.

**Ordering information****DS1109i Glassbreak Detector**

Mounts to door or window frames. Includes an internal magnetic contact.

Order number **DS1109i**

**Represented by:****Americas:**

Bosch Security Systems, Inc.  
130 Perinton Parkway  
Fairport, New York, 14450, USA  
Phone: +1 800 289 0096  
Fax: +1 585 223 9180  
security.sales@us.bosch.com  
www.boschsecurity.us

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com