

II-1300-9

**INSTALLATION INSTRUCTIONS FOR SERIES 1330 EMERGENCY RELEASE
COVERS THE FOLLOWING MODELS:**

- 1330-2 EMERGENCY RELEASE COLOR BLUE, PROVIDES MANUAL EMERGENCY REPORTING.
MOUNTS IN A STANDARD SINGLE GANG BOX 2 1/8" DEEP.
UL LISTED 8P05 FIRE ALARM BOX.
STATE OF CALIFORNIA LISTING 7150-1477-101 BOXES PULL STATIONS.

ELECTRICAL SPECIFICATIONS

- 1 AMP @ 30 VDC, 0.1 AMP @ 120 VAC
- MAXIMUM WIRE SIZE 12 AWG

EMERGENCY RELEASE FUNCTION

PULLING ON THE HANDLE WILL RELEASE THE INTERNAL SWITCHES TO CONTROL ANY PERIPHERAL DEVICE.
IF OPTIONAL BREAK GLASS IS USED IT WILL BREAK WHEN HANDLE IS PULLED, GLASS REPLACEMENT INSTRUCTIONS ARE SHOWN ON INSIDE OF HANDLE.

RESETTING EMERGENCY RELEASE

RESETTING IS ACCOMPLISHED BY INSERTING A 1/8" SCREWDRIVER
FROM FRONT THROUGH HOLE.

