



Accessories

RELAYS

Door Release and External Light Activation Relays

RY-PA



DOOR RELEASE RELAY:

- Selectively release one or more doors with the LEF system (LEF-3L, plus all 5- and 10-call LEF masters)
 - Each door to be released requires a separate RY-PA
 - Also used for LDF, NDR, TB-M/D systems (SOP)
- Connect an electric door strike to the VC-M system

EXTERNAL SIGNALING:

- Activate a doorbell or buzzer when a call is received at a VC-K handset in a VC-M system

SPECIFICATIONS:

Power Source:	Supplied by system
Relay Switching Capacity:	1A @ 24V DC or 0.3A @ 240V AC.
External Device Reqsmts:	Normally open dry contact
Dimensions (HxWxD):	110V AC or 24V DC door strike 2-1/8" x 1-3/8" x 7/8"

MAW-B



EXTERNAL LIGHT ACTIVATION RELAY:

- Activate a light at the door station to illuminate entry area
 - MY Video systems using the MYW-P3CB or MYW-P3L
 - K-Series Color Video Systems
 - VY Multi-Unit Video Entry system

DOOR RELEASE RELAY:

- For integration of another manufacturer's electric door strike
 - VY Multi-Unit Video Entry system

SPECIFICATIONS:

Power Source:	Supplied by system
Relay Switching Capacity:	1A @ 24V DC or 0.3A @ 240V AC
Contact Closure:	Normally open dry contact
Dimensions (HxWxD):	Light Activation: While camera is on Door Release: While door release button is pressed 4-1/16" x 2-1/4" x 1-3/8"