



RS101S Remote Sounder Tone Speakers



Shown with red Call-Placed light illuminated

Architects' And Engineers' Specifications

Remote tone sounder station(s) shall be Alpha Communications® model **RS101S** or approved equal.

The **RS101S** stations shall include a built-in Tone Speaker mounted behind a rugged 2mm thick Natural Anodized Aluminum faceplate. The **RS101S** shall be also include an internal Red Tone Lamp and double-contact momentary Tone-Off pushbutton.

RS101S tone sounder stations shall provide remote audible and visual annunciator when used in conjunction with Alpha Communications® **AlphaEcall™** 100 series annunciator and **AC219** Control Unit, or similar system.

The **RS101S** shall protrude from the finished wall surface a maximum of 1.3875" (35mm), and shall be only 3.25" wide (83mm).

Contractor shall observe all local and national electrical and building codes.

RS101S Remote Tone Sounder Station

The **RS101S** remote tone sounder stations provide for remote audible and visual annunciation when connected directly in parallel with an Alpha Communications® **AlphaEcall™** 100 series annunciator and **AC219** control unit, or **CM800** or **DS100** series annunciator and **PK2019** / **PK2019A** control unit. The **RS101S** stations feature a momentary contact Tone-Off button for tone silencing. Depressing the Tone-Off button silences the tone at all sounding locations. When the emergency initiating device has been reset, the Tone-Off will automatically reset. The **RS101S** also includes a red Call-Placed light which will illuminate when an initial call is placed on the Alpha Communications® **AlphaEcall™** 100 series system.

Features

- Easy installation - fully surface mount
- Red Call-Placed light (concealed)
- Pushbutton Tone-Off reset
- Reliable and rugged 2mm thick Aluminum faceplate
- Advanced design

Specifications

Dimensions:	Height: 6.875" (175mm) Width: 3.25" (83mm) Depth: 1.375" (35mm) at it's deepest point on the surface housing
Finish:	Natural Anodized Aluminum faceplate
Controls:	Individually replaceable push button with self-wiping double contacts
Indicator:	28 volt red light (concealed)
Tone Speaker:	50-ohms, Round (50mm)
Connections:	Pigtails
Housing:	Hi-impact plastic, surface mount housing included

42 Central Drive • Farmingdale • NY • 11735-1202 • Phone: (631) 777-5500 • Fax: (631) 777-5599
TOLL-FREE: (800) 666-4800 • Web: AlphaCommunications.com • Email: info@alphacommunications.com

Copyright© 1998-2014 Alpha Communications® - All Rights Reserved.

Due to continuous product improvement, all colors, sizes, materials, finishes and specifications are subject to change without notice. [Next \(APS800\) >](#)

[< Previous \(APS798\)](#)