

MODEL TS-25

EMERGENCY DOOR RELEASE



METHOD OF OPERATION

PRESSING THE LATCHING PUSHBUTTON WILL SOUND THE BUZZER AND LIGHT THE SWITCH.THE CONTACTS WILL TRANSFER PROVIDING A CIRCUIT TO RELEASE THE DOOR.PRESSING THE PUSHBUTTON AGAIN WILL RETURN THE DOOR TO THE LOCKED POSITION AND TURN OFF THE LIGHT AND BUZZER.

- RED .675 x .875 INCH RECTANGULAR PUSHBUTTON
- PUSHBUTTON LABELED "PUSH"
- PLATE LABELED "EMERGENCY DOOR RELEASE,ALARM WILL SOUND
- S.P.D.T. LATCHING ILLUMINATED PUSHBUTTON
- CONTACTS RATED 3A. @ 35 VDC OR 120 VAC
- 85 Db PIEZO BUZZER
- 12 OR 24 VOLT DC OPERATION



ALARM CONTROLS CORPORATION
19 BRANDYWINE DRIVE DEER PARK, NY 11729

1 631 586-4220 1 800 645-5538
WWW.ALARMCONTROLS.COM EMAIL INFO@ALARMCONTROLS.COM

**MODEL TS-25
EMERGENCY DOOR RELEASE
INSTALLATION WIRING**

YELLOW	POSITIVE 12 VDC
BLACK	NEGATIVE 12 VDC
WHITE	COMMON
BLUE	NORMALLY-OPEN
RED	NORMALLY-CLOSED



ALARM CONTROLS CORPORATION
DEER PARK, NEW YORK 11729