

VISTA-40

The feature-rich VISTA-40 Control Panel is a cost-effective solution for almost any application. Features include advanced partitioning, end-user simplicity and compatibility with the best wireless technology today.

A powerful control, the VISTA-40 can support residential installations and operate lights and appliances — providing you with greater installation flexibility while offering your customers the ultimate in convenience.



**Control
Panel**

FEATURES:

Dependable features to meet your most demanding installations:

- Nine hardwired zones, expandable to 64 zones
- Two partitions with seven authority levels
- 70 user codes
- 100 event alarm history log
- Two-way downloading
- Supports 16 two-wire smoke detectors and 16 keypads
- Three technology options:
 - Standard hardwired, expander 4208U (eight zones) 4190WH (two zones)
 - ADEMCO polling loop addressable devices
 - Wireless (5800 series)
- Supports up to eight relays
- Supports X-10 transformer (Part No. 4300)
- Long Range Radio triggers (four)

End users will appreciate the easy-to-use convenience and control features of the VISTA-40:

- Wireless remote controls (featuring single button system operation):
 - 5804 - Four-button programmable wireless key
 - 5804BD - Bi-directional four-button programmable wireless key with system status feedback
- Single or dual-button wireless personal panic: 5802MN and 5802MN2
- Home automation activates lights, appliances, garage doors, and numerous other devices
- The Vista Interactive Phone Module (VIP) gives the end-user control of the system from any touchtone phone; the 4286VIP responds in clear English, with over a 100 word vocabulary
- Full English display keypads clearly communicate system status and zone locations

**ADEMCO
GROUP**

VISTA-40

SPECIFICATIONS:

Electrical:

- Aux power 12VDC, 750 max.
- 16.5VAC/40 VA transformer
- Alarm output 12VDC, 1.7 amps max
- For UL installations, combined Aux and alarm output cannot exceed 750mA

Output Control:

- Supports up to two relay boards (Part No. 4204)
- Each relay board supports four relays for a total of eight
- Optional X-10 transformer/interface (part number 4300) may be used to control X-10 receiving devices

Zones:

- Nine hardwired zones
- Selectable response on zone 9: 10msec or 500msec
- Assignable to either partition
- 14 zone types to choose from
- Programmable swinger suppression
- Expandable to 64 zones using 5800 wireless, or hardwired expansion

Communications:

- Touchtone or pulse
- Formats supported: ADEMCO Contact ID, ADEMCO 4 + 2 Express, ADEMCO low speed
- 3+1, 4+1 and 4+2 reporting
- Reporting capabilities: Split, Dual, Split/Dual
- Low battery reports 11.2-11.6VDC
- Expanded reporting
- Up to four digit PABX code supported
- True dial tone detection
- Double pole line seizure
- AC loss and restoral reporting supported

ORDERING:

Part No.	Description
VISTA-40	Control Panel

SUPPORTED DEVICES

Hardwired Expansion Devices:

- 4208U up to eight zones - 25 mA
- 4204 up to eight relays - 15mA (each active relay draws 40mA)
- Powerline support - 4300 transformer/interface
- Keypads
 - 6139 custom English (required for programming) - 100mA
 - 6128 fixed English LCD - 30mA
- Voice Module 4286VIP - 160mA
- Two-wire smoke detectors
- V-Plex™ polling loop devices and keyswitch devices

Wireless Receiver Systems:

- 5800 Receivers
 - 5881ENL up to 8 zones - 50mA
 - 5881ENM up to 16 zones - 50mA
 - 5881ENH up to 64 zones - 50mA
- All receivers support:
 - Diversity reception with two antennas
 - Remote mounting for best location
 - A second receiver for maximum coverage or tough installations
 - Unique supervision and low battery indications by point

Transmitters:

- 5800 Series - three volt lithium batteries, one mile range, tamper standard

Agency Listings:

- UL Residential Fire and Burglary and CFM
- Commercial Burglary (with VISTA-UL kit)

**Control
Panel**

165 Eileen Way, Syosset, NY 11791

Copyright ©2002 Pittway Corporation

ADEMCO is an ISO9001 Registered Company

**ADEMCO
GROUP**