

6160PX

ALPHA DISPLAY KEYPAD WITH INTEGRATED PROXIMITY READER



Honeywell's 6160PX Custom Alpha Prox Keypad is easy to install and simple to use. The system can be armed away or disarmed with a single swipe of the proximity tag, making operation effortless while reducing false alarms. Prox keypad can be installed in hardwired or wireless installations. Security code is incorporated into the prox tag for easy enrollment.

The 6160PX also features a large, bright 32-character display with easy-to-read plain-English status messages. The oversized function keys are easily accessible even when the keypad door is closed, and can be programmed for fire, burglary, personal emergencies and other operations. Colored self-adhesive labels are included to easily identify one-button functions.

FEATURES

- Integrated proximity reader
- Two lightweight tags included with user code already incorporated
- Arming (armed away) and disarming functions
- Large, easy-to-use keypad
- Keys continuously backlit for greater visibility
- Zones and system events displayed in plain English
- Speaker with audible beeps to indicate:
 - System status
 - Entry/exit delay
 - Other alarm situations
- Four programmable function keys
- System functions clearly labeled
- White console blends with any décor

SPECIFICATIONS

Physical

- 5-5/16"H x 7-3/8" W x 1-3/16" D (135mm x 190mm x 30mm)

Displays

- 2 x 16 alpha-numeric supertwist LCD, backlit

Sounder

- Speaker (fire alarm is loud, pulsing single tone; burglary alarm is loud, continuous, dual-tone)

Voltage

- 12VDC (power-limited)

Current

- Activated transmission – 165mA (ARMED LED lit, LCD backlight and sounder on)
- Standby – reduces to 40mA when panel is operating in standby mode (backlight off)

Wiring

- - (Black): Ground
- + (Red): +12 VDC (Aux. Power)
- D1 (Green): "Data in" to control panel
- D0 (Yellow): "Data out" from control panel

Compatibility

- Fully compatible with all addressable VISTA controls

Agency Listings

- ETL Listings:
- Residential Fire and Burglary
 - Commercial Burglary

ORDERING

6160PX	Alpha Display Keypad with Integrated Proximity Reader
PROXTG-BK	Black Prox Tag
PROXTG-GY	Gray Prox Tag

Automation and Control Solutions

Honeywell Security & Communications
2 Corporate Center Dr. Suite 100
P.O. Box 9040
Melville, NY 11747
1.800.467.5875
www.honeywell.com

Honeywell

L/6160PXD/D
September 2010
© 2010 Honeywell International Inc.