



## **Fan Heat** 400-650W

- Compact fan heater in PTC technology
  - Maintains minimum operating temperatures in enclosures
  - Helps to prevent failure of electronic components caused by condensation and corrosion
- Heating power adjusts to ambient temperature
- Integrated adjustable thermostat and control light
- DIN rail mountable

Technical Data CR 027						
			Max. current	Axial Fan		
Part No.	<u>Voltage</u>	Power <sup>1)</sup>	(inrush)	(ball bearing)	Thermostat range	<u>Weight</u>
02700.0-00	220-240 VAC	400W (50 Hz)	11A	20 cfm (35 m <sup>3</sup> /h)	0 - 60°C	2 lbs/0.9 kg
02701.0-00	220-240 VAC	550W (50 Hz)	13A	26 cfm (45 m³/h)	0 - 60°C	2.4 lbs/1.1 kg
02700.9-00	100-120 VAC	550W (60 Hz)	14A	20 cfm (35 m³/h)	32 - 140°F	2 lbs/0.9 kg
02701.9-00	100-120 VAC	650W (60 Hz)	15A	26 cfm (45 m³/h)	32 - 140°F	2.4 lbs/1.1 kg
1)		′				

than listed is applied.

" at 68°F (20°C) ambient tempe	rature. Also, power will vary when frequency other
Heating element:	PTC-semiconductor/resistor, self-regulating with
	changing ambient temperature (see graph below)
Overheat protection:	Built-in temperature limiter in case of fan failure
Function control light:	LED
Housing:	Plastic, UL94V-0
Dimensions (H x W x D):	6.5 x 3.94 x 5" (165 x 100 x 128mm)
Connection:	2-pole terminal, AWG 14 max. (2.5 mm <sup>2</sup> )
Mounting:	Clip for 35 mm DIN rail (EN 50022)
Protection class:	II (double insulated)
Protection type:	IP 20
Vaeucy approvale:	TIII

## Wiring note:

Heater includes 3 terminals: L, N1, and N2. The power supply Line is connected to "L" and the Neutral to "N1" - Terminal N2 is not used. Also, a Ground wire is not required as the heater is made of double-insulated plastic.

Determining the required heater size:

$$P_H = (A \times T \times k) - P_V$$

P<sub>H</sub> = Required heating power for your application in Watts (W)

 $P_{\nu}$  = Heating power generated by existing components (e.g. a transformer) in Watts (W)

A = Exposed enclosure surface area in square meters (m<sup>2</sup>)


T = Temperature differential between the desired minimum interior temperature and the Lowest possible external temperature of the enclosure in Kelvin (K), 1.8°F = 1°C = 1K

= Heat transmission coefficient of the enclosure material used:


5.5W/m<sup>2</sup>K Painted steel: Stainless steel: 3.7W/m<sup>2</sup>K Polyester/Plastic:  $3.5W/m^2K$ 


For outdoor applications it is recommended to double the heating power.

For spacing, add 2" clearance to heat sensitive parts.









CR027/03-07/US

Specifications are subject to change without notice. Suitability of this product for its intended use and any associated risks must be determined by the end customer/buyer in its final application.