

INTERCOM SUB-STATIONS

K-LR-3W Sub-Station with Call Button

Description

This 2-way indoor/outdoor call-originating speaker is designed for hands-free operation with any Talk-A-Phone manual master intercom system.

Features

- · Weather-proof speaker
- 2-way speaker/microphone
- · In non-private mode press button to call, then speak hands-free
- In private mode press button to talk, release to listen
- Requires no separate power source
- Simple 3-conductor connection
- · Stainless steel face plate



Dimensions: Face plate: 4.81(122) W x 7.19(183) H in(mm)

Wall Opening: 4.13(105) W x 6.50(165) H x 2(51) D in(mm)

Construction: Stainless steel face plate, hermetically sealed push button

Weight: 3 lbs. (1.4kg)

Mounting: Flush mounts; use **K-SM-L** surface mount accessory to surface mount

Power: 2 watt capacity, powered by Master

Cable: 1 shielded pair

Options & Accessories

Surface Mount Box: Use model K-SM-L to surface mount

Cable: Use model **6303** to connect to Talk-A-Phone manual masters

Feedback elimination: Order model K-LR-3W(C) instead of K-LR-3W when master is to be placed in close

proximity to sub-station

Desktop Sub-Station: Order model K-LR-3 for a desk-top version of the K-LR-3W

