# **FLY KIT**

## COMPACT PASSIVE INFRARED REQUEST TO EXIT SENSOR





















Reduces False Detections by Detecting Both Presence and a Change in Temperature

#### DESCRIPTION

BEA's Fly Kit is the industry's most compact passive infrared (PIR) sensor, ideal for request to exit (REX) applications. The Fly Kit is part of the portfolio of request to exit products, including presence sensors, power supplies, heavy duty piezo devices, illuminated buttons, access keypads, maglocks and other peripheral devices.

This low-cost, versatile sensor can be flush or surface mounted into any door, ceiling or wall. This flexibility and low profile make it an effective sensor for managing building security and traffic flow.

## FEATURES & BENEFITS

- Sensing field adjustment masks provide accurate detection zones (2 included)
- DIP switches for user-defined settings
- Extended Relay Time (ERT) version is available for hold times of 15 or 30 seconds
- Compact, aesthetically pleasing design
- Packages include both ceiling and surface mount adapters



BEA, Inc. RIDC Park West 100 Enterprise Drive Customer Service: 800.523.2462 Technical Support: 800.407.4545

Pittsburgh, PA 15275-1213 www.BEAinc.com













MAGLOCKS

BR3 LOGIC MODULE

**ELECTRIC STRIKES** 

POWER SUPPLIES

#### TECHNICAL SPECIFICATIONS

Technology	Passive Infrared
Mounting Height	Recommended: 78 to 96 in (6.5 ft to 8 ft) Maximum: 120 in (10 ft)
Mounting Angles	0° to 180°
Power Supply	12 to 24 VAC; ±10%; (50/60 Hz) 12 to 24 VDC; -10% / +30%
<b>Current Consumption</b>	<10 mA (20 mA if the relay output is activated)
Contact Rating	1 A / 75 VDC or 50 VAC potential free contact NO/NC
Optical Characteristics	Four element passive infrared with independent masking possibilities
Warm-up Time	10 s
Response Time	Maximum: 200 ms
Relay Hold Time	
Standard Fly	0.5 or 2 s
Fly Extended Relay Time	15 or 30 s
Operating Temperature	-22°F to +140°F (-30°C to +55°C)
Cable	108 inches of 4-conductor cable with 5-pin connector
Weight	1.4 oz (40 g)

 $4.0 \text{ in} \times 1.0 \text{ in} \times 1.8 \text{ in}$ 

#### SERIES BREAKDOWN

10FLYKITB - INCLUDES: 10FLYBLK, 10FSABLK, 10FCABLK 10FLYKITBERT - INCLUDES: 10FLYBLKERT, 10FSABLK, 10FCABLK

#### FLY KIT COMPONENTS (not sold separately)







10FLYBLKERT **EXTENDED RELAY** TIME - BLACK



10FSABLK FLY SURFACE ADAPTER - BLACK



10FCABLK **FLY CEILING** ADAPTER - BLACK




SENSING FIELD ADJUSTMENT MASK





70.0011 108" CABLE

## DIMENSIONAL DRAWINGS

Sensor Dimensions (LxW×H)







www.BEAinc.com © 2015 BEA, Inc. All rights reserved.

FLY KIT COMPACT PASSIVE INFRARED REQUEST TO EXIT SENSOR

BEA, Inc. RIDC Park West 100 Enterprise Drive Pittsburgh, PA 15275-1213 Technical Support: 800.407.4545

Customer Service: 800.523.2462



